



The Signal Jammer

# TSJ-4GCGW

4G Portable Compact



- Before turning on the device you must install the antennas according to the indicated positions on the handset
  - (1) CDMA/GSM: 850 to 960MHz
  - (2) DCS: 1805 to 1880MHz or DCS/PCS:1805 to 1990MHz
  - (3) 3G: 2,110 to 2,170MHz
  - (4) 4G1 LTE:725-770MHZ OR 790-862 MHz
  - (5) 4G2 2345-2400MHz or 2620-2690 MHz
- CDMA/GSM/DCS/PCS,3G,4GLTE/WIMAX, You can select 6 of above frequency bands you need in a jammer
- Total output power is 2.5W. Each band can adjust to ON or OFF power
- Jamming range: up to 20m.
- Jamming radius depends on the strength signal in local area
- External Omni-directional antennas for TX frequency covered down link only

- Power supply: 50 to 60Hz, 100 to 240V AC
- With AC adapter (AC100-240V-DC12V),4000mA/H battery
- Dimension: 126x76x35mm and not include antennas
- Weight: 0.65kg
  
- Advantages:
  - Multiple bands, Can adjust ON or OFF any single band without influencing the other bands operation.
  - High output power
  - Cooling fan inside, Can be used in car with car charger and AC charger
  - Built-in Battery:4000mA/h. Full charge time about 4 Hours.
  - Operational time on a full charge: 1-2 Hours.
  
- Application Area:
  - For some locations of special purpose such as hospitals, gas stations, etc. Please field test first to make sure no interference occurs to the normal operation of equipment and instruments
  
- Warranty: One year from delivery date.
  
- Where noted - frequencies are given as an example, as custom tuning and geolocation may determine different frequency programming.